
iView Update Instructions

This download will upgrade iView application. Detailed information about the changes in the application can be found in the release notes.

Automatic Update Instructions

1. Format a USB pen drive no larger than 4 GB using a Windows PC as "FAT32".
2. Copy the contents of the archive to the USB pen drive. Do not copy the contents to the root folder of the drive directly; do not create or modify any folders manually. E.g. the folder named "InstallerFiles" must be visible directly on the pen drive's drive letter (e.g. "H:\InstallerFiles\").
3. Insert the USB pen drive into your Handheld.
4. Power off the printer.
5. Power the printer on again.
6. The update is performed automatically. Follow the instructions on the screen.

Manual Update Instructions

If the automatic update does not function (e.g. because your Handheld has not previously had the iView application installed) you can still use this download to manually install the iView and PR4 applications.

Simply insert the USB pen drive and restart the printer by turning it off and on again.

The updater will display a message informing you that no updates could be performed. After confirming the message, the updater will display a user interface.

Press the „Programs“ button at the top right and select any programs you wish to install or remove, then press the corresponding „Remove“ or „Install“ buttons.

When the installation is complete, press the button labeled „Reboot now“ and remove the USB pen drive to resume normal operations.

History

Version	Change	Date	Author
1.0	TI created	5.7.2013	Kunz
1.1	TI update for iView 1.1.0.7	4.9.2013	Kunz/Balling
1.2	TI generalized	19.2.2014	Balling